


Oppgave 30 – Løsning:

a)

Dad:		A	B	C	D	E	
	A E:	1	-	-	-	A	
	B A:	B	2	-	-	A	
	C A:	B	C	3	-	A	
	E D:	C	C	4	C	C	Path Compression (2 stk)
	C E:	C	C	4	C	C	(ingenting skjer)

Resulterende skog:



b)

Dad:		A	B	C	D	E	F	(ingen PC skjer!)
	B C:	-	C	1	-	-	-	
	A E:	E	C	1	-	1	-	
	D B:	E	C	2	C	1	-	
	B F:	E	C	F	C	1	3	
	E C:	E	C	F	C	F	5	

Resulterende skog:

